

## DIST-ED2

### LED antipanic modul konstantna struja

- Antipanic modul rezervno napajanje sa baterijom nudi 60-180 minuta rada nakon nestanka električne energije.
- Konstantna struja.
- Baterija LiFePO4



RoHS CE



| Model       | Snaga  | Izlazni napon              | Izlazna struja         | Autonomija | Baterija                | Test mod |
|-------------|--------|----------------------------|------------------------|------------|-------------------------|----------|
| DIST-ED2-HO | 6W max | 10-50V                     | 120mA<br>100mA<br>80mA | 1 h        | LiFePO4<br>6.4V1500mAh  | AT/MT    |
| DIST-ED2-HO | 6W max | 10-50V                     | 120mA<br>100mA<br>80mA | 3 h        | LiFePO4 6.4V<br>4500mAh | AT/MT    |
| DIST-ED2-ST | 4W Max | 10-60V                     | 70mA<br>60mA<br>50mA   | 1 h        | LiFePO4<br>6.4V1500mAh  | AT/MT    |
| DIST-ED2-ST | 4W Max | 10-60V                     | 70mA<br>60mA<br>50mA   | 3 h        | LiFePO4<br>6.4V3300mAh  | AT/MT    |
| DIST-ED2-LO | 2W Max | 40-60V<br>20-40V<br>10-30V | 35mA<br>50mA<br>70mA   | 1 h        | LiFePO4<br>6.4V600mAh   | AT/MT    |
| DIST-ED2-LO | 2W Max | 40-60V<br>20-40V<br>10-30V | 35mA<br>50mA<br>70mA   | 3 h        | LiFePO4<br>6.4V1500mAh  | AT/MT    |